

INSTRUCTION MANUAL SPHERO

TIME MOVER® TECHNOLOGY






BUBEN&ZORWEG

INSTRUCTION MANUAL SPHERO

TIME MOVER® TECHNOLOGY

To get the most out of your new SPHERO watch winder and take full advantage of its features, we are pleased to provide you with some valuable tips.



INSERTING THE WATCH

- Ensure your SPHERO watch winder is turned off.
- Open the glass plate to access the inside.
- Slowly pull the watch holder out of the slot using the side handles (Fig. 1).
- Press in and hold the back section of the watch holder (Fig. 2) so that the watch can be placed over it with either an open or closed strap.
- Ensure the watch strap is closed. Insert the watch holder back into your device until it snaps into place.

We do not accept liability for damage to watches, straps or bracelets due to improper handling. We provide a 5-year warranty on the TIME MOVER® technology.

POWERED BY BATTERY

There is a cover plate on the back.

- Carefully unscrew this plate in the centre (Fig. 3).
- Insert two type C batteries (baby cells).
- Make sure the positive and negative terminals are aligned with the markings.
- Carefully screw the plate back on.

POWERED BY ELECTRICITY

The device features a USB-C port for direct connection to a power supply.

The USB-C port is not intended for charging batteries. A compatible USB-C cable and power adapter are not included in the scope of delivery.

TECHNICAL DATA

- Dimensions: 122 x 149 x 158 mm (H x W x D)
- Weight: 2.2 kg
- Technology: TIME MOVER®
- Capacity: one watch

SETTINGS

The watch winder is equipped with patented TIME MOVER® technology and offers the following settings via the central on/off  button:

- Number of rotations per day

Using the left button  you can select 900, 1200 or 1500 rotations per day.

- Direction of rotation

The right button  sets the direction of rotation: left, right or automatically alternating in both directions ('Left & Right').

Press the on/off button  to start or stop the device once settings are selected.

SLEEP PHASE

After 16 hours of operation, the watch winder automatically pauses for the next 8 hours. The 16-hour operating period begins when the on/off button  is pressed.



GERMAN
DESIGN
AWARD
WINNER
2018



GERMAN
DESIGN
AWARD
WINNER
2020

ERNST & YOUNG
TOP30 GERMAN
LUXURY BRANDS
2016 & 2018



International Diamond Prize for
Excellence in Quality
WINNER 2019



german
brand
award
17
winner



german
brand
award
18
winner



german
brand
award
19
winner



german
brand
award
24
winner

Buben & Zörweg Manufaktur GmbH

Andreas-Odenwald-Weg 5 | 75177 Pforzheim | Germany
+49 (0)7231 205 880 | info@buben-zorweg.com
buben-zorweg.com

